



This product can instead of the card single door access machine, no need to reform;

The communication way: RS485、 TCP/IP、 USB flash disk and USB line, 4P port on the back of the machine is TCP/IP port;

This product can be used as single access machine, also can be used as fingerprint scanner link into the access controller (WG26/34) ;

After up gradate machine, if the port and the diagram on the back of the machine is different, please according to the newest wiring diagram;

The relay of this access control is DC24V3A, if the door access control directly connects with the lock, please pay attention to the nominal. The alarm output port is DC 12V, it can be linked with 12V security alarm, and no need to add other power adapter.

This product also can be used to attendance administration, installed the fingerprint time attendance software, and link the machine and computer with one of the communication ways.

Lock_NO	Lock signal NO port	12V	12Vpower output
Lock_COM	Lock signal common port	WG_IN 1	Weigand input positive
Lock_NC	Lock signal NC port	WG_IN 0	WG input negative
Button	Exit	GND	land
GND	land	D_Sensor	Door Magnetic Input port
WG_Out 1	WG output positive	GND	land
WG_Out 0	WG negative output	Alarm+	An external electronic doorbell
GND	Land	Alarm -	
Bell+	An external electronic doorbell	GND	land
Bell+		12V Power	Power input

